使用指南

北架构》信息技术有限公司 - 闪闪(1284323)

接入步骤

短信模板申请

接入

术有限公司 - 闪闪(1284323) 短信发送的生命周期

接口文档

状态回调


备注

概述

国内短信,适用于短信验证码,短信通知,营销短信等场景;支持三大运营商,虚拟运营商短信发送,电

https://market.aliyun.com/products/57126001/cmapi00039729.html? spm=5176.730005.productlist.d cmapi00039729.729435240jeRcl&innerSource=search %E5%8 C%97%E4%BA%AC%E4%B8%80%E7%A0%82#sku=yuncode3372900001

架构



接入步骤

购买套餐 -> 申请短信模板,获得短信模板ID -> 调试接入 -> 上线使用

短信模板申请

北京一砂信息技术有限公司 - 闪闪(1284323) 按照国家相关法律规定,发送短信验证码、短信通知、营销短信等需要先提交给运营商审核、审核通 过后才可发送短信。

短信模板分成两部分: 1. 短信签名, 2.短信模板, 如"【一砂】验证码为: [{0}], 欢迎登陆平台!", 【一砂】部分为短信签名、剩余部分为短信模板。


短信签名要求是公司的名称,软件名称等,最好语义明确,不可盗用他人签名,否则提交审核时容易。4323 被拒。

短信模板分成固定部分和可变参数部分,可变参数部分的格式为 {n}, 其中n指的是第n个参数。

接入

短信发送的生命周期

如下 北京一砂信息技术有限公司 - 闪闪(1284323)



可参考阿里云文档

状态回调

短信发送为异步发送,最终的结果通过异步回到的方式通知业务服务器,回调的url为传入参数 callbackUrl, 回调的报文格式如下:

```
1 {
      "reference_id":"65CA48A0752012689190921055936659",
3
      "external_id":"5122f7d8a93f11ea8b6700163e02db87",
      "status":{
5
          "updated on":"2020-06-08T04:20:09.873298Z",
6
          "code":200,
          "description": "Delivered to handset"
      }
8
9 }
```

状态码如下:

状态码	Associated Text String	描述
200	Delivered to handset	The SMS was delivered to the end user's phone. (Final)
京一砂信	息技术有限	北京一砂信息技术有限

状态码	Associated Text String	描述
203	Delivered to gateway	The SMS was delivered to the gateway. If the gateway responds with further information (including successful delivery to handset or delivery failure), the status is updated. (Intermediate)
207	Error delivering SMS to handset (reason unknown)	The SMS could not be delivered to the end user's handset for an unknown reason. (Final)
210	Temporary phone error	The SMS could not be delivered to the handset due to a temporary error with the phone. Examples – phone is turned off, not enough memory to store the message. (Final)
211	Permanent phone error	The SMS could not be delivered to the handset due to a permanent error with the phone. For example, the phone is incompatible with SMS, or illegally registered on the network. This can happen when a phone number is blacklisted, or is incorrectly provisioned. (Final)
220	Gateway/network cannot route message	The network cannot route the message to the handset. (Final)
221	Message expired before delivery	The message was queued by the mobile provider and timed out before it could be delivered to the handset. (Final)
222	SMS not supported	SMS is not supported by this phone, carrier, plan, or user.
229	Message blocked by your request	TeleSign blocked the SMS before it was sent. This is due to your prior submitted request to blocklist this phone number.
230	Message blocked by TeleSign	TeleSign blocks a message if it is being sent to a phone number that is on a global blocklist.
231	Invalid/unsupported	The content of the message is not supported.
234	Price threshold exceeded	Message not sent due to the price exceeding your set maximum price.
237	Message blocked in requested country	You requested that messages in a specific country be blocked, and the message was being sent to this country.
238	Destination blocked by prefix	You requested that phone numbers with a particular prefix be blocked.
250	Final status unknown	The final status of the SMS cannot be determined.
286	Transaction not attempted	The SMS is blocked from being sent due to the phone type not being one of the following – mobile, prepaid, personal, or pager.

状态码	Associated Text String	描述
290	Message in progress	The message is being sent to the SMS gateway.
292	Queued by gateway	The SMS gateway has queued the message.
295	Status delayed	The status of the SMS is temporarily unavailable.
500	Transaction not attempted	No SMS request was attempted.
502	Campaign error	This error can be generated if there is a problem with the short code used.
503	Carrier rejected – temporary problem	This error is generated if there is an error on the carrier or operator side that is temporary and the message can be retried.
504	Carrier rejected – permanent error	This error is generated if there is an error on the carrier or operator side that is permanent and the message should not be retried.
505	Error on gateway – temporary error	This error is generated if there is an error on TeleSign's partner side that is considered temporary and the message can be retried.
506	Error on gateway – permanent error	This error is generated if there is an error on TeleSign's partner side that is considered permanent and the message should not be retried.
507	Invalid destination address	There is a problem with the destination address used. Either the format is not valid, or the number is not associated with any carrier, or if MSC is used it does not know about this MSISDN.
508	Invalid source address	The message requires a source address. Verify that one is provided and correct.
510	Message blocked by subscriber action or request	The end user has blocked receiving SMS with their carrier plan or by request or from the particular short code used.
511	Subscriber low on credit	The end user exceeded their spending limits and cannot receive SMS.
512	Roaming error	End user cannot receive SMS because their device that receives the messages is roaming.
513	Mobile number portability error	SMS failed because ported combinations are unreachable.
514	Subscriber absent	The operator/carrier is temporarily unable to reach the end user.
515	Suspected spam	This message is considered to be spam by carrier or operator.

状态 码	Associated Text String	描述
599	Status not available	The system is unable to provide status at this time.

备注

- 2. 短信模板审核需要大约2天的时间,在短信过审中,我们可以先调试,在短信模板和签名过审钱,签名默认为【PIN】,并放在短信的未足 北京一砂信息技术